

# How to Transfer the Phonebook

## 1. Use the receiver to set the phonebook transfer-wait mode.

### For the KD-BT11

#### 1-1. Phone Key -> SETTINGS -> PHONEBOOK

- \* It is not necessary for mobile phones with source phonebooks to be "paired" in advance.
- \* Phonebook transfer may not be possible with certain "paired" mobile phones. In these situations, remove the "paired" settings from both devices before attempting phonebook transfer.
- \* The KD-BT11 will not memorize pairing information from a non-paired mobile phone.

#### 1-2. Input pincode

- \* The default setting is 0000; users can create their own pincode using up to sixteen numerical digits.
- \* The pincode must be identical to the one for the "Send" function of the mobile phone used for phonebook transfer.

#### 1-3. After pincode input, the receiver will be set in the transfer-wait mode as shown below.

- \* Any connected phone will be disconnected when the transfer-wait mode is set.
- \* The first 50 phonebook entries previously registered will be displayed in chronological order.
- \* "FULL" will be displayed on the screen after 50 entries are received.

Transfer-wait mode



When the number of phonebook entries reaches memory capacity (50 entries)



## 2. Using the mobile phone to transfer the phonebook

- \* For conventional mobile phones, phonebooks can be transferred by displaying Phonebook, going to Options and selecting Bluetooth as the transfer method.
- \* The mobile phone source of the phonebook must be equipped with the Bluetooth OPP function.
- \* Individual entries, groups, and/or the entire phonebook can be selected and transferred; actual operation may vary depending on the type of mobile phone used.

## For the Motorola V3x

2-1 Display Phonebook, go to Options, select Send Contact, and use Bluetooth as the method.



2-2. As with conventional pairing (Object Exchange), the phone will search for Bluetooth devices for transfer and list them.



2-3. Choose the KD-BT11 from the list and input the pincode to initiate transfer.



**2-4. Phonebook transfer will begin automatically when both pincodes correspond.**



**For the NOKIA 6230i**

- 1. Go to "Names".**
- 2. Choose the address(es) that you wish to transfer to the phone.**
- 3. Go to "Detail".**
- 4. Go to "Option".**
- 5. Select "Send business card".**
- 6. Go to "Select".**
- 7. Select "via Bluetooth".**
- 8. Go to "Select".**

### **3. Receiver operation and displays**

#### **3-1. During phonebook transfer**

One entry transferred



10 entries transferred



When 50 entries are transferred, the screen will show RECEIVED and automatically return to its normal display.



### 3-2. Exiting the transfer-wait mode during phonebook transfer

Phonebook transfer operation can be terminated before 50 entries are transferred by pressing the BACK key (UP key on the KD-BT11).